DECEMBER 1983-REVISED MARCH 1988

- Package Options Include Plastic "Small Outline" Packages, Ceramic Chip Carriers and Flat Packages, and Plastic and Ceramic DIPs
- Dependable Texas Instruments Quality and Reliability


#### description


These devices contain 4-wide AND-OR-INVERT gates. They perform the following Boolean functions:

'54 Y = 
$$\overrightarrow{AB}$$
 +  $\overrightarrow{CD}$  +  $\overrightarrow{EF}$  +  $\overrightarrow{GH}$   
LS54 Y =  $\overrightarrow{AB}$  +  $\overrightarrow{CDE}$  +  $\overrightarrow{FGH}$  +  $\overrightarrow{IJ}$ 


The SN5454 and SN54LS54 are characterized for operation over the full military temperature range of  $-55\,^{\circ}\text{C}$  to 125 $\,^{\circ}\text{C}$ . The SN7454 and SN74LS54 are characterized for operation from 0 $\,^{\circ}\text{C}$  to 70 $\,^{\circ}\text{C}$ .

#### logic diagrams (positive logic)







SN5454 . . . W PACKAGE (TOP VIEW)



SN54LS54 . . . J OR W PACKAGE SN74LS54 . . . D OR N PACKAGE (TOP VIEW)




SN54LS54 . . . FK PACKAGE (TOP VIEW)




NC-No internal connection
NU-Make no external connection

# SN5454, SN54LS54, SN7454, SN74LS54 4-WIDE AND-OR-INVERT GATES


## logic symbols†






positive logic:  $Y = \overline{AB + CDE + FGH + IJ}$ 

## schematics





Resistor values shown are nominal.

The portion of the circuits within the dashed lines is repeated for each additional 2- or 3-input AND section, as shown in the logic diagram and logic symbols.

<sup>&</sup>lt;sup>†</sup>These symbols are in accordance with ANSI/IEEE Std 91-1984 and IEC Publication 617-12. Pin numbers shown are for D, J, and N package. For the SN54LS54 only, they apply also for the W package.

## absolute maximum ratings over operating free-air temperature range (unless otherwise noted)

Supply voltage, VCC (see Note	1)	7 V
Input voltage		5.5 V
Operating free-air temperature:	SN5454	-55°C to 125°C
	SN7454	0°C to 70°C
Storage temperature range		-65°C to 150°C

NOTE 1: Voltage values are with respect to network ground terminal.

## recommended operating conditions

			SN5454				SN7454			
		MIN	NOM	MAX	MIN	NOM	MAX	UNIT		
Vcc	Supply voltage	4.5	5	5.5	4.75	5	5.25	V		
VIH	High-level input voltage	2			2			٧		
VIL	Low-level input voltage			9.0			8.0	٧		
	High-level output current			- 0.4		-	- 0.4	mΑ		
IOL	Low-level output current			16			16	mA		
	Operating free-air temperature	<b>– 55</b>		125	0		70	°C		

## electrical characterics over recommended operating free-air temperature range (unless otherwise noted)

	TEST CONSTITUTE		SN5454				SN7454			
PARAMETER	TEST CONDITIONS†	MIN	TYP‡	MAX	MIN	TYP ‡	MAX	UNIT		
ViK	V <sub>CC</sub> = MIN. I <sub>1</sub> = - 12 mA			- 1.5			- 1.5	V		
νон	VCC = MIN, VIL = 0.8 V, IQH = -	0.4 mA 2	4 3.4		2.4	3.4		V		
VOL	V <sub>CC</sub> = MIN. V <sub>1H</sub> = 2 V, I <sub>OL</sub> = 10	mA	0.2	0.4	]	0.2	0.4	٧		
I <sub>I</sub>	V <sub>CC</sub> = MAX, V <sub>I</sub> = 5.5 V			1			1	mA		
ΊΗ	V <sub>CC</sub> = MAX, V <sub>I</sub> = 2.4 V			40			40	μΑ		
l L	V <sub>CC</sub> = MAX, V <sub>1</sub> = 0.4 V			- 1.6			- 1.6	mA		
losÿ	V <sub>CC</sub> = MAX	- 2	0	<b>– 55</b>	- 18		<b>– 55</b>	mA		
Іссн	V <sub>CC</sub> = MAX, V <sub>I</sub> = 0 V		4	8		4	8	mΑ		
ICCL	V <sub>CC</sub> = MAX, See Note 2		5.1	9.5		5.1	9.5	mΑ		

<sup>†</sup> For conditions shown as MIN or MAX, use the appropriate value specified under recommended operating conditions.

## switching characteristics, VCC = 5 V, TA = 25°C (see note 3)

PARAMETER	FROM (INPUT)	TO (OUTPUT)	TEST CONDITIONS	MIN TY	P MAX	UNIT
†PLH	0	V	$R_1 = 400 \Omega$ , $C_1 = 15 pF$	1	3 22	ns
tPHL.	Апу	· · · · · · · · · · · · · · · · · · ·	A[ - 400 32,		8 15	ns -

NOTE 3: Load circuits and voltage waveforms are shown in Section 1.

<sup>‡</sup> All typical values are at  $V_{CC}$  = 5 V,  $T_A$  = 25°C.

<sup>§</sup> Not more than one output should be shorted at a time.

NOTE 2: All inputs of one AND gate at 4.5 V, all others at GND.

# SN54LS54, SN74LS54 4-WIDE AND-OR-INVERT GATES

## absolute maximum ratings over operating free-air temperature range (unless otherwise noted)

Supply voltage, VCC (see Note	1)	 	 	 	7 '	٧
Input voltage		 	 	 <b>.</b>	7 '	٧
Operating free-air temperature:	SN54LS54	 	 	 	-55°C to 125°	С
	SN74LS54	 	 	 	0°C to 70°C	С
Storage temperature range		 	 	 	-65°C to 150°C	С

NOTE 1: Voltage values are with respect to network ground terminal.

#### recommended operating conditions

		S	SN54LS54			SN74LS54			
		MIN	NOM	MAX	MIN	NOM	MAX	UNIT	
Vcc	Supply voltage	4.5	5	5.5	4.75	5	5.25	V	
VIH	High-level input voltage	2			2			٧	
VIL	Low-level input voltage			0.7			8.0	V	
ІОН	High-level output current			- 0.4			- 0.4	mA	
OL	Low-level output current			4			8	mΑ	
τ <sub>A</sub>	Operating free-air temperature	- 55		125	0		70	°c	

## electrical characteristics over recommended operating free-air temperature range (unless otherwise noted)

PARAMETER	!	S	N54LS	i4	S					
	•	TEST CONDIT	MIN	TYP \$	MAX	MIN	TYP ‡	MAX	דומט	
Vικ	VCC = MIN,	l <sub>1</sub> = 18 mA				- 1.5			- 1.5	* V
Voн	VCC = MIN,	VIL = MAX,	OH = - 0.4 mA	2.5	3.4	-	2.7	3.4		V
VOL	V <sub>CC</sub> = MIN,	V <sub>(H</sub> = 2 V,	IOL = 4 mA		0.25	0.4		0.25	0.4	
• OL	V <sub>CC</sub> = MIN	V <sub>IH</sub> = 2 V,	IOL = 8 mA					0.35	0.5	<b>'</b>
lj	VCC = MAX,	V <sub>1</sub> = 7 V				0.1			0.1	mA
ЧН	V <sub>CC</sub> = MAX,	V <sub>1</sub> = 2.7 V				20			20	μА
	V <sub>CC</sub> = MAX,	V <sub>1</sub> = 0.4 V		7		- 0.4			- 0.4	mA
losş	V <sub>CC</sub> = MAX	<u></u> -		- 20		- 100	- 20		<b>– 100</b>	mΑ
Іссн	V <sub>CC</sub> = MAX,	V; = 0 V			8.0	1.6		8.0	1.6	mΑ
<sup>1</sup> CCL	V <sub>CC</sub> = MAX,	See Note 2			1	2		1	2	mΑ

<sup>†</sup> For conditions shown as MIN or MAX, use the appropriate value specified under recommended operating conditions.

## switching characteristics, VCC = 5 V, TA = 25°C (see note 3)

PARAMETER	FROM (INPUT)	TO (OUTPUT)	TEST CONDITIONS	MIN	TYP	MAX	UNIT
t <b>P</b> LH	Anv	v	$R_1 \approx 2 k\Omega$ , $C_1 = 15 pF$		12	20	ns
<sup>t</sup> PHL				[	12.5	20	ns

NOTE 3: Load circuits and voltage waveforms are shown in Section 1.



 $<sup>^{\</sup>ddagger}$  All typical values are at VCC = 5 V, TA = 25°C.

<sup>§</sup>Not more than one output should be shorted at a time, and the duration of the short-circuit should not exceed one second.

NOTE 2: All inputs of one AND gate at 4.5 V, all others at GND.





15-Apr-2017

#### **PACKAGING INFORMATION**

Orderable Device	Status	Package Type	Package	Pins	Package	Eco Plan	Lead/Ball Finish	MSL Peak Temp	Op Temp (°C)	Device Marking	Samples
	(1)		Drawing		Qty	(2)	(6)	(3)		(4/5)	
SN5454J	ACTIVE	CDIP	J	14	1	TBD	A42	N / A for Pkg Type	-55 to 125	SN5454J	Samples
SN54LS54J	ACTIVE	CDIP	J	14	1	TBD	A42	N / A for Pkg Type	-55 to 125	SN54LS54J	Samples
SN54LS54J	ACTIVE	CDIP	J	14	1	TBD	A42	N / A for Pkg Type	-55 to 125	SN54LS54J	Samples
SNJ5454J	ACTIVE	CDIP	J	14	1	TBD	A42	N / A for Pkg Type	-55 to 125	SNJ5454J	Samples
SNJ5454J	ACTIVE	CDIP	J	14	1	TBD	A42	N / A for Pkg Type	-55 to 125	SNJ5454J	Samples
SNJ54LS54J	ACTIVE	CDIP	J	14	1	TBD	A42	N / A for Pkg Type	-55 to 125	SNJ54LS54J	Samples
SNJ54LS54J	ACTIVE	CDIP	J	14	1	TBD	A42	N / A for Pkg Type	-55 to 125	SNJ54LS54J	Samples
SNJ54LS54W	ACTIVE	CFP	W	14	1	TBD	A42	N / A for Pkg Type	-55 to 125	SNJ54LS54W	Samples
SNJ54LS54W	ACTIVE	CFP	W	14	1	TBD	A42	N / A for Pkg Type	-55 to 125	SNJ54LS54W	Samples

(1) The marketing status values are defined as follows:

**ACTIVE:** Product device recommended for new designs.

LIFEBUY: TI has announced that the device will be discontinued, and a lifetime-buy period is in effect.

NRND: Not recommended for new designs. Device is in production to support existing customers, but TI does not recommend using this part in a new design.

PREVIEW: Device has been announced but is not in production. Samples may or may not be available.

**OBSOLETE:** TI has discontinued the production of the device.

TBD: The Pb-Free/Green conversion plan has not been defined.

**Pb-Free (RoHS):** TI's terms "Lead-Free" or "Pb-Free" mean semiconductor products that are compatible with the current RoHS requirements for all 6 substances, including the requirement that lead not exceed 0.1% by weight in homogeneous materials. Where designed to be soldered at high temperatures, TI Pb-Free products are suitable for use in specified lead-free processes. **Pb-Free (RoHS Exempt):** This component has a RoHS exemption for either 1) lead-based flip-chip solder bumps used between the die and package, or 2) lead-based die adhesive used between

the die and leadframe. The component is otherwise considered Pb-Free (RoHS compatible) as defined above.

Green (RoHS & no Sb/Br): TI defines "Green" to mean Pb-Free (RoHS compatible), and free of Bromine (Br) and Antimony (Sb) based flame retardants (Br or Sb do not exceed 0.1% by weight

in homogeneous material)

<sup>(2)</sup> Eco Plan - The planned eco-friendly classification: Pb-Free (RoHS), Pb-Free (RoHS Exempt), or Green (RoHS & no Sb/Br) - please check http://www.ti.com/productcontent for the latest availability information and additional product content details.

<sup>(3)</sup> MSL, Peak Temp. - The Moisture Sensitivity Level rating according to the JEDEC industry standard classifications, and peak solder temperature.

<sup>(4)</sup> There may be additional marking, which relates to the logo, the lot trace code information, or the environmental category on the device.



# **PACKAGE OPTION ADDENDUM**

15-Apr-2017

(5) Multiple Device Markings will be inside parentheses. Only one Device Marking contained in parentheses and separated by a "~" will appear on a device. If a line is indented then it is a continuation of the previous line and the two combined represent the entire Device Marking for that device.

(6) Lead/Ball Finish - Orderable Devices may have multiple material finish options. Finish options are separated by a vertical ruled line. Lead/Ball Finish values may wrap to two lines if the finish value exceeds the maximum column width.

**Important Information and Disclaimer:** The information provided on this page represents TI's knowledge and belief as of the date that it is provided. TI bases its knowledge and belief on information provided by third parties, and makes no representation or warranty as to the accuracy of such information. Efforts are underway to better integrate information from third parties. TI has taken and continues to take reasonable steps to provide representative and accurate information but may not have conducted destructive testing or chemical analysis on incoming materials and chemicals. TI and TI suppliers consider certain information to be proprietary, and thus CAS numbers and other limited information may not be available for release.

In no event shall TI's liability arising out of such information exceed the total purchase price of the TI part(s) at issue in this document sold by TI to Customer on an annual basis.

# W (R-GDFP-F14)

# CERAMIC DUAL FLATPACK



NOTES:

- A. All linear dimensions are in inches (millimeters).
- B. This drawing is subject to change without notice.
- C. This package can be hermetically sealed with a ceramic lid using glass frit.
- D. Index point is provided on cap for terminal identification only.
- E. Falls within MIL STD 1835 GDFP1-F14



CERAMIC DUAL IN LINE PACKAGE



Images above are just a representation of the package family, actual package may vary. Refer to the product data sheet for package details.

4040083-5/G





CERAMIC DUAL IN LINE PACKAGE



#### NOTES:

- 1. All controlling linear dimensions are in inches. Dimensions in brackets are in millimeters. Any dimension in brackets or parenthesis are for reference only. Dimensioning and tolerancing per ASME Y14.5M.
- 2. This drawing is subject to change without notice.
- 3. This package is hermitically sealed with a ceramic lid using glass frit.
- His package is remitted by sealed with a ceramic its using glass mit.
   Index point is provided on cap for terminal identification only and on press ceramic glass frit seal only.
   Falls within MIL-STD-1835 and GDIP1-T14.



CERAMIC DUAL IN LINE PACKAGE



#### **IMPORTANT NOTICE**

Texas Instruments Incorporated (TI) reserves the right to make corrections, enhancements, improvements and other changes to its semiconductor products and services per JESD46, latest issue, and to discontinue any product or service per JESD48, latest issue. Buyers should obtain the latest relevant information before placing orders and should verify that such information is current and complete.

TI's published terms of sale for semiconductor products (http://www.ti.com/sc/docs/stdterms.htm) apply to the sale of packaged integrated circuit products that TI has qualified and released to market. Additional terms may apply to the use or sale of other types of TI products and services.

Reproduction of significant portions of TI information in TI data sheets is permissible only if reproduction is without alteration and is accompanied by all associated warranties, conditions, limitations, and notices. TI is not responsible or liable for such reproduced documentation. Information of third parties may be subject to additional restrictions. Resale of TI products or services with statements different from or beyond the parameters stated by TI for that product or service voids all express and any implied warranties for the associated TI product or service and is an unfair and deceptive business practice. TI is not responsible or liable for any such statements.

Buyers and others who are developing systems that incorporate TI products (collectively, "Designers") understand and agree that Designers remain responsible for using their independent analysis, evaluation and judgment in designing their applications and that Designers have full and exclusive responsibility to assure the safety of Designers' applications and compliance of their applications (and of all TI products used in or for Designers' applications) with all applicable regulations, laws and other applicable requirements. Designer represents that, with respect to their applications, Designer has all the necessary expertise to create and implement safeguards that (1) anticipate dangerous consequences of failures, (2) monitor failures and their consequences, and (3) lessen the likelihood of failures that might cause harm and take appropriate actions. Designer agrees that prior to using or distributing any applications that include TI products, Designer will thoroughly test such applications and the functionality of such TI products as used in such applications.

TI's provision of technical, application or other design advice, quality characterization, reliability data or other services or information, including, but not limited to, reference designs and materials relating to evaluation modules, (collectively, "TI Resources") are intended to assist designers who are developing applications that incorporate TI products; by downloading, accessing or using TI Resources in any way, Designer (individually or, if Designer is acting on behalf of a company, Designer's company) agrees to use any particular TI Resource solely for this purpose and subject to the terms of this Notice.

TI's provision of TI Resources does not expand or otherwise alter TI's applicable published warranties or warranty disclaimers for TI products, and no additional obligations or liabilities arise from TI providing such TI Resources. TI reserves the right to make corrections, enhancements, improvements and other changes to its TI Resources. TI has not conducted any testing other than that specifically described in the published documentation for a particular TI Resource.

Designer is authorized to use, copy and modify any individual TI Resource only in connection with the development of applications that include the TI product(s) identified in such TI Resource. NO OTHER LICENSE, EXPRESS OR IMPLIED, BY ESTOPPEL OR OTHERWISE TO ANY OTHER TI INTELLECTUAL PROPERTY RIGHT, AND NO LICENSE TO ANY TECHNOLOGY OR INTELLECTUAL PROPERTY RIGHT OF TI OR ANY THIRD PARTY IS GRANTED HEREIN, including but not limited to any patent right, copyright, mask work right, or other intellectual property right relating to any combination, machine, or process in which TI products or services are used. Information regarding or referencing third-party products or services does not constitute a license to use such products or services, or a warranty or endorsement thereof. Use of TI Resources may require a license from a third party under the patents or other intellectual property of the third party, or a license from TI under the patents or other intellectual property of TI.

TI RESOURCES ARE PROVIDED "AS IS" AND WITH ALL FAULTS. TI DISCLAIMS ALL OTHER WARRANTIES OR REPRESENTATIONS, EXPRESS OR IMPLIED, REGARDING RESOURCES OR USE THEREOF, INCLUDING BUT NOT LIMITED TO ACCURACY OR COMPLETENESS, TITLE, ANY EPIDEMIC FAILURE WARRANTY AND ANY IMPLIED WARRANTIES OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE, AND NON-INFRINGEMENT OF ANY THIRD PARTY INTELLECTUAL PROPERTY RIGHTS. TI SHALL NOT BE LIABLE FOR AND SHALL NOT DEFEND OR INDEMNIFY DESIGNER AGAINST ANY CLAIM, INCLUDING BUT NOT LIMITED TO ANY INFRINGEMENT CLAIM THAT RELATES TO OR IS BASED ON ANY COMBINATION OF PRODUCTS EVEN IF DESCRIBED IN TI RESOURCES OR OTHERWISE. IN NO EVENT SHALL TI BE LIABLE FOR ANY ACTUAL, DIRECT, SPECIAL, COLLATERAL, INDIRECT, PUNITIVE, INCIDENTAL, CONSEQUENTIAL OR EXEMPLARY DAMAGES IN CONNECTION WITH OR ARISING OUT OF TI RESOURCES OR USE THEREOF, AND REGARDLESS OF WHETHER TI HAS BEEN ADVISED OF THE POSSIBILITY OF SUCH DAMAGES.

Unless TI has explicitly designated an individual product as meeting the requirements of a particular industry standard (e.g., ISO/TS 16949 and ISO 26262), TI is not responsible for any failure to meet such industry standard requirements.

Where TI specifically promotes products as facilitating functional safety or as compliant with industry functional safety standards, such products are intended to help enable customers to design and create their own applications that meet applicable functional safety standards and requirements. Using products in an application does not by itself establish any safety features in the application. Designers must ensure compliance with safety-related requirements and standards applicable to their applications. Designer may not use any TI products in life-critical medical equipment unless authorized officers of the parties have executed a special contract specifically governing such use. Life-critical medical equipment is medical equipment where failure of such equipment would cause serious bodily injury or death (e.g., life support, pacemakers, defibrillators, heart pumps, neurostimulators, and implantables). Such equipment includes, without limitation, all medical devices identified by the U.S. Food and Drug Administration as Class III devices and equivalent classifications outside the U.S.

TI may expressly designate certain products as completing a particular qualification (e.g., Q100, Military Grade, or Enhanced Product). Designers agree that it has the necessary expertise to select the product with the appropriate qualification designation for their applications and that proper product selection is at Designers' own risk. Designers are solely responsible for compliance with all legal and regulatory requirements in connection with such selection.

Designer will fully indemnify TI and its representatives against any damages, costs, losses, and/or liabilities arising out of Designer's non-compliance with the terms and provisions of this Notice.